


TABLE A  
FILTER (OPTIONAL)

Type Filter		Filter Leads	Filter Lead Termination
302G	5302G		
61P or 61L	61S	BK	BK of Dial
		Y	Y of Dial
		R	Filter bracket terminal. Also, disconnect BR-Y lead from Y of dial and reconnect to filter bracket terminal.

TABLE B  
LINE AND RINGER CONNECTIONS

Wire or Lead	Individual or Bridged	
	Wire	Lead
Mounting Cord in Set	R	L1
	G	L2Y
	Y	Gnd
Ringer Leads	R	L1
	BK	K
Mounting Cord at Connecting Block	R	R
	G	G
	Y	Y
Line Wire at Connecting Block	Ring	R
	Tip	G
	Grd	Y

APPARATUS BLANK  
82A



DERIVED FROM:  
BELL SYSTEM PRACTICES  
SECTION 502-400-401  
Issue 2, November, 1961

SIMPLIFIED & REFORMATTED  
FOR VIEWING ON SCREEN  
11-29-05 STEPH KERMAN

**Note 1:** To permanently silence ringer, connect both red and black ringer leads to K terminal.

**Note 2:** When a G-type hand set is used with the 5302G, telephone set, connect red and one white conductor of hand set cord to R terminal of induction coil.

**TELEPHONE SETS—302E, G, 5302G  
COMMON BATTERY — CONNECTIONS**